



Features

- **Clip-on lavalier mic provides articulate, full-sounding voice pickup**
- **Also excels as an instrument mic, especially for pickup of acoustic guitar with included AT8444 instrument adapter**
- **Cardioid polar pattern reduces pickup of sounds from the sides and rear, improving isolation of desired sound source**
- **Offers the convenience of battery or phantom power operation**
- **Rugged design and construction for reliable performance**
- **Switchable 80 Hz high-pass filter minimizes pickup of undesired low-frequency sounds**

Description

The PRO 70 is a miniature clip-on/lavalier condenser microphone with a cardioid polar pattern. It is designed for quality sound reinforcement, professional recording, television and other demanding sound pickup applications.

The microphone is intended to be worn on the clothing or used as an instrument mic for excellent yet unobtrusive sound pickup. The wide-range capability of the microphone ensures clean, accurate reproduction with high intelligibility for speakers and presenters as well as for instrument pickup. Its small size makes it ideal for use in applications where minimum visibility is required.

The microphone requires 11V to 52V phantom power or a 1.5V AA battery for operation. A battery need not be in place for phantom power operation.

The microphone's cardioid polar pattern provides a 120° angle of acceptance.

The microphone includes a 1.8 m (6') permanently attached miniature cable. Its free end connects to the provided AT8531 power module via a TA3F-type connector. The output of the power module is a 3-pin XLRM-type connector.

A 3-position switch in the power module permits choice of off, on/flat response or on/low-roll-off (via integral 80 Hz high-pass filter). The roll-off position reduces the pickup of low-frequency ambient noise.

The microphone comes equipped with a power module, a clothing clip, an instrument adapter, a windscreen, a battery and a soft protective pouch.

Operation and Maintenance

The PRO 70 requires 11V to 52V phantom power or a 1.5V AA battery for operation. A battery need not be in place for phantom power operation.

To install the battery, remove the cap from the top of the power module. Insert a fresh 1.5V AA battery ("+" end toward the cap release button), then reassemble the power module. For longest battery life, the switch should remain off except when the microphone is in use. Alkaline batteries are recommended for longest life. Remove the battery during long-term storage.

Output is low impedance (Lo-Z) balanced. The signal appears across Pins 2 and 3; Pin 1 is ground (shield). Output phase is "Pin 2 hot"—positive acoustic pressure produces positive voltage at Pin 2.

To avoid phase cancellation and poor sound, all mic cables must be wired consistently: Pin 1-to-Pin 1, etc.

A 3-position switch in the power module permits choice of off, on/flat response, or on/low-roll-off (via integral 80 Hz high-pass filter). The roll-off position reduces the microphone's sensitivity to popping in close vocal use. It also reduces the pickup of low-frequency ambient noise (such as traffic, air-handling systems, etc.), room reverberation and mechanically coupled vibrations. To engage the filter, slide the switch toward the "bent" line. To turn the microphone on without engaging the filter, slide the switch toward the flat line.

For use as a lavalier, attach the microphone about six inches below the chin. Anticipate movements that may cause the microphone to rub against or be covered by clothing, and position the microphone to avoid it.

Avoid leaving the microphone in the open sun or in areas where temperatures exceed 110° F (43° C) for extended periods. Extremely high humidity should also be avoided.

To reduce the environmental impact of a multi-language printed document, product information is available online at www.audio-technica.com in a selection of languages.

Afin de réduire l'impact sur l'environnement de l'impression de plusieurs langues, les informations concernant les produits sont disponibles sur le site www.audio-technica.com dans une large sélection de langue.

Para reducir el impacto al medioambiente, y reducir la producción de documentos en varios leguajes, información de nuestros productos están disponibles en nuestra página del Internet: www.audio-technica.com.

Para reduzir o impacto ecológico de um documento impresso de várias linguas, a Audio-Technica providência as informações dos seus produtos em diversas linguas na www.audio-technica.com.

Per evitare l'impatto ambientale che la stampa di questo documento determinerebbe, le informazioni sui prodotti sono disponibili online in diverse lingue sul sito www.audio-technica.com.

Der Umwelt zuliebe finden Sie die Produktinformationen in deutscher Sprache und weiteren Sprachen auf unserer Homepage: www.audio-technica.com.

Om de gevolgen van een gedrukte meertalige handleiding op het milieu te verkleinen, is productinformatie in verschillende talen "on-line" beschikbaar op: www.audio-technica.com.

本公司基於減少對環境的影響，將不作多語言文件的印刷，有關產品訊息可在 www.audio-technica.com 的官方網頁上選擇所屬語言及瀏覽。

本公司基于减少对环境的影响，将不作多语言文档的印刷，有关产品信息可在 www.audio-technica.com 的官方网页上选择所属语言和浏览。

자원 절약, 환경 보호를 위해 국문 사용 설명서는 인쇄하지 않았습니다.
제품 정보는 www.audio-technica.com 에서 원하는 언어 선택 후에 다운로드 받으실 수 있습니다.

Specifications

Element	Fixed-charge back plate, permanently polarized condenser
Polar pattern	Cardioid
Frequency response	100-14,000 Hz
Low frequency roll-off	80 Hz, 12 dB/octave
Open circuit sensitivity	Phantom: -45 dB (5.6 mV) re 1V at 1 Pa Battery: -45 dB (5.6 mV) re 1V at 1 Pa
Impedance	Phantom: 200 ohms Battery: 200 ohms
Maximum input sound level	Phantom: 123 dB SPL, 1 kHz at 1% T.H.D. Battery: 123 dB SPL, 1 kHz at 1% T.H.D.
Dynamic range (typical)	Phantom: 96 dB, 1 kHz at Max SPL Battery: 96 dB, 1 kHz at Max SPL
Signal-to-noise ratio¹	67 dB, 1 kHz at 1 Pa
Phantom power requirements	11-52V DC, 2 mA typical
Battery type	1.5V AA/UM3
Battery current / life	0.4 mA / 1200 hours typical (alkaline)
Switch	Off, on-flat, on-roll-off
Weight	Microphone: 0.3 oz (8 g) Power module: 4.7 oz (134 g)
Dimensions	Microphone: 25.0 mm (0.98") long, 10.2 mm (0.40") diameter Power module: 83.0 mm (3.27") H x 63.0 mm (2.48") W x 22.0 mm (0.87") D
Output connector	Integral 3-pin XLRM-type
Cable	Integral 6' (1.8 m), permanently attached between microphone and power module
Audio-Technica case style	M1
Accessories furnished	AT8411 clothing clip; AT8444 instrument adapter; power module; windscreen; battery; soft protective pouch

In the interest of standards development, A.T.U.S. offers full details on its test methods to other industry professionals on request.


1 Pascal = 10 dynes/cm² = 10 microbars = 94 dB SPL

¹ Typical, A-weighted, using Audio Precision System One.


Specifications are subject to change without notice.



frequency response: 100–14,000 Hz



polar pattern



 **audio-technica**

Audio-Technica Corporation
audio-technica.com ©2017 Audio-Technica

P51684-02